

Fixture Type: _____

Catalog Number: _____

Project: _____

Location: _____

Enclosed Electronic Transformer

120V/12V Class 2 Power Supply

Model & Product

EN-12120-RB2 Enclosed Electronic Class 2 Transformer 120V Input 12V Output 2 x 60W = 120W
EN-12180-RB2 Enclosed Electronic Class 2 Transformer 120V Input 12V Output 3 x 60W = 180W
EN-12300-RB2 Enclosed Electronic Class 2 Transformer 120V Input 12V Output 5 x 60W = 300W
EN-1260-RB2 Enclosed Electronic Class 2 Transformer 120V Input 12V Output 60 Watt

L x W x H

6IN x 3.25IN x 2.625IN
6.75IN x 3.625IN x 2.625IN
8.25IN x 4.625IN x 2.625IN
6.625IN x 1.625IN x 1.25IN

Example: **EN-12120-RB2**

DESCRIPTION

UL & cUL listed electronic transformer is the perfect solution for wiring multiple low voltage fixtures. WAC transformers are intrinsically safer transformers because they are compartmentalized to allow no greater than 5 amps of current to be drawn on each compartment. Secondary wiring for transformers do not require conduit sheathed cable or clamp wiring techniques. This transformer has a low minimum load requirement of 1W to allow the use of LED products. May be dimmed using an electronic low voltage dimmer.

FEATURES

- 1W minimum load
- Use for all initial installations to ensure safe and primary side connections in a wiring compartment
- Dimming with Electronic Low Voltage dimmers
- All connections must be made in an enclosure for proper installations
- Secondary wiring for Class 2 transformers does not require conduit sheathed cable or clamp wiring techniques
- Non-metallic sheathed cable may be used for secondary wiring in walls and ceilings
- Drop down to a smaller gauge wire if space in fixture does not permit secure connection directly with the non-metallic sheathed cable
- Built-in auto reset, soft start, short and overload circuit
- 5 year warranty

SPECIFICATIONS

Input: 120 VAC, 50/60Hz
Finish: Black
Operating Temp: -40°F to 122°F (-40°C to 50°C)
Standards: UL, cUL



FINISHES:



Black